





1. Unpack the luminaire.




2. Screw the auxiliary securing cable to the luminaire..



3. Attach the luminaire fixture to the designated location using a suitable connecting material.



4. Using a carabiner, attach the other end of securing cable to the prepared point.




5. Unscrew the ballast box



6. Use a suitable tool (e.g., a screwdriver) to make an opening in the cable gland.




7. Feed the power supply cable through the cable gland.




8. Connect the power supply cable.




9. wiring - 2 core cable.
Recommended cable -rubber cable
H07RN-F 2Dx1mm2



10. Tighten the cable glands and screw the cover back on.





11. Remove the cap from the side of the luminaire, adjust the luminaire to the desired angle. Tighten the screws and close the cap.





Dimensional diagram of NITRON 1



 = 21 kg

Recommended installation height
up to 20 meters.

- If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.

- The light sources in this luminaire is only replaceable by the manufacturer or their technicians or a qualified person.

- This luminaire operates at mains voltage 220-240V, 50-60 Hz.

- Any modification to this luminaire is forbidden.

Cleaning:

clean the luminaire with the standard detergents. DO NOT use any abrasive detergents or solvents.

Installation and maintenance:

can provide only a person with an electrical qualification.

ELEKTRO-LUMEN, s. r. o.
Hranická 505
753 61 Hranice IV - Drahotuše
Česká republika

Telefon: +420 581 699 411
Fax: +420 581 699 419
E-mail: el-lumen@el-lumen.cz
Web: www.el-lumen.cz



The company reserves the right to change technical data and printing errors.
Copyright © ELEKTRO-LUMEN, s. r. o.